

## CODICI COLORI CABLAGGI

In wiring diagrams, the individual wire colours are noted with codes:

**B** : solid Black.

**B/U** : Black, with a thin Blue *tracer* colour running along it.

The Colours are as follows:

|          |         |          |                |          |
|----------|---------|----------|----------------|----------|
| B= Black | N=Brown | R=Red    | O=Orange       | Y=Yellow |
| G=Green  | U=Blue  | P=Purple | LG=Light Green | K=Pink   |
| S=Slate  | W=White |          |                |          |

Physically, the colours used follow a fairly fixed pattern:

**Solid Color:** from Supply, runs to switch

**Striped:** from Switch, runs Between switch and component  
Note: Same color as solid = same system

**Black:** from Component runs to Ground

**Black with Stripes:** from Component runs Switch on ground side of component

| Colors         | Abbrev. | System                                | Examples                              |
|----------------|---------|---------------------------------------|---------------------------------------|
| Brown          | N       | Battery feed wire - <b>Hot</b> always | To ammeter, ign. switch, light switch |
| Yellow         | Y       | Generator                             | usually with brown                    |
| White          | W       | Ignition switch <b>On</b>             | to ign. coil, tach                    |
| Whitew/Red     | WR      |                                       | to starter solenoid                   |
| Green          | G       | Fused - Ignition switch <b>On</b>     | to gauges, turn signals               |
| Green w/Red    | GR      |                                       | LH turn signal                        |
| Green w/White  | GW      |                                       | RH turn signal                        |
| Green w/Purple | GP      |                                       | brake lights                          |
| Green w/Brown  | GN      |                                       | reverse lights                        |
| Purple         | B       | Fused- <b>Hot</b> always              | lighter, courtesy lights              |
| Blue           | U       | Headlights                            | to relays                             |
| Blue w/Red     | UR      |                                       | low beams                             |

|               |     |                          |                          |
|---------------|-----|--------------------------|--------------------------|
| Blue w/White  | UW  |                          | high beams               |
| Red           | R   | Running lights           | to side lamps            |
| Red w/Yellow  | RY  |                          | driving/fog lamps        |
| Black         | B   | Ground                   | to battery negative      |
| Other         |     |                          |                          |
| Pink          | K   |                          |                          |
| Slate         | S   |                          |                          |
| Black w/crust | SZL | Battery Drain - Hot once | to ground from battery + |